



**RICOH IM 550/600/600SR Enhanced Security
Firmware**

Common Criteria Guide

Version 1.0

March 2023

Document prepared by



www.lightshipsec.com

Table of Contents

1	About this Guide	4
1.1	Overview	4
1.2	Audience	4
1.3	About the Common Criteria Evaluation	4
1.4	Conventions	8
1.5	Related Documents	8
2	Secure Acceptance and Update	10
2.1	Obtaining the TOE	10
2.2	Verifying the TOE	10
2.3	Power-on Self-Tests	10
2.4	Updating the TOE	10
3	Configuration Guidance	12
3.1	Installation	12
3.2	Administration Interfaces	12
3.3	Initial Configuration	12
3.4	Services	34
3.5	Administration	34
3.6	Management of Security Functions	36
3.7	U_NORMAL User Access	42
4	Clearing the machine for redeployment or at end-of-life	42

List of Tables

Table 1: TOE Models	4
Table 2: Machine Firmware and Hardware for TOE version E-1.00-H.	5
Table 3: Drivers	6
Table 4: Evaluation Assumptions	8
Table 5: Related Documents	8
Table 6: System Settings 1	14
Table 7: Basic Authentication	21
Table 8: LDAP Authentication	21
Table 9: Printer Settings.....	22
Table 10: Scanner Settings	23
Table 11: Fax Settings	23
Table 12: Device Settings	25
Table 13: Printer Settings.....	26
Table 14: Fax Settings	27
Table 15: Network Settings	27
Table 16: Security Settings	28
Table 17: Wim Auto Logout Settings.....	32
Table 18: System Settings 2	32
Table 19: Fax Settings	33
Table 20: Management Functions.....	35
Table 21: Changing System Settings	36
Table 22: SMTP Settings	39
Table 23: Changing Security Settings	39
Table 24: Auto Logout Settings.....	41
Table 25: Audit Events	43

.

1 About this Guide

1.1 Overview

- 1 This guide provides supplemental instructions to achieve the Common Criteria evaluated configuration of the RICOH IM 550/600/600SR Enhanced Security Firmware and related information.

1.2 Audience

- 2 This guide is intended for system administrators and the various stakeholders involved in the Common Criteria evaluation. It is assumed that readers will use this guide in conjunction with the related documents listed in Table 5.

1.3 About the Common Criteria Evaluation

- 3 The Common Criteria for Information Technology Security Evaluation (ISO/IEC 15408) is an international standard for security certification of IT products and systems. More information is available at <https://www.commoncriteriaportal.org/>

1.3.1 Protection Profile Conformance

- 4 The Common Criteria evaluation was performed against the requirements of the Protection Profile for Hardcopy Devices (HCD PP) v1.0 and Protection Profile for Hardcopy Devices, v1.0, Errata #1, June 2017 available at <https://www.niap-ccavs.org/Profile/PP.cfm>

1.3.2 Evaluated Software and Hardware

- 5 The TOE includes the RICOH MFP models: RICOH IM 550/600/600SR Enhanced Security Firmware labeled and marketed under different Ricoh Family Group brand names as noted in **Table 1**.
- 6 The TSF is executed by the main controller and the operation unit respectively. For all TOE models, the main controller has an Intel Goldmont CPU and runs LPUX 6.0 OS, a customized OS based on NetBSD; the operation unit has an ARM Cortex-A9 Quad Core processor and runs a customized Linux 3.18 OS.
- 7 The first two numeric digits in the TOE model number correspond to copy speed, e.g. 550 performs 55 copies per minute, 600 performs 60 copies per minute, the alphabetic suffix corresponds to regional fonts and printer languages.
- 8 Differences between models with different printing speeds are limited to print engine components; differences between branding variants are limited to labels, displays, packaging materials, and documentation. The differences are not security relevant. All TOE models are version E-1.00-H Table 2 below lists the names and version of the firmware components that make-up the TOE firmware; and Table 3 identifies printer and fax drivers included in the TOE.

Table 1: TOE Models

Branding	TOE Models
RICOH	IM 550F, IM 600F, IM 600SRF, IM 600SRFG

Branding	TOE Models
SAVIN, LANIER	IM 550F, IM 600SRF, IM 600SRFG
nashuatec, Rex Rotary, Gestetner	IM 550F, IM 600F, IM 600SRF

Table 2: Machine Firmware and Hardware for TOE version E-1.00-H.

Primary Classification	Secondary Classification	Version
Firmware	System/Copy	5.37
	Network Support	18.86
	Web Support	4.00.3
	Fax	05.31.00
	Scanner	05.02
	Web Uapl	4.00.2
	NetworkDocBox	5.34
	animation	3.00
	Printer	5.34
	GraphicData	2.04
	MovieData	1.01
	MovieData2	1.01
	MovieData3	1.01

Primary Classification	Secondary Classification	Version
	Data Erase Onb	1.05
	GWFCU3.8-21(WW)	08.00.00
	RicohACT	2.1
	Cheetah System	5.37.00
	decolet	3.01.00
	iwnnimeml	2.8.201
	simpleprinter	1.01
	smartcopy	1.02
	smartdocumentbo	1.02
	smartfax	1.04
	smartprtstoredj	1.01
	smartscanner	1.01
	stopwidget	2.02
Hardware	Ic Ctlr	03
	Ic Key	01024704

Table 3: Drivers

Drivers	Model
Printer Driver	PCL6 Driver 1.54.0.0
LAN-Fax Driver	LAN-Fax Driver 9.5

1.3.3 Evaluated Functions

9

The following functions have been evaluated under Common Criteria:

- a) **Security Audit.** The TOE generates audit records of user and administrator actions. It stores audit records both locally and on a remote syslog server.
- b) **Cryptographic Support.** The TOE includes a cryptographic module for the cryptographic operations that it performs. The relevant CAVP certificate numbers are noted in the Security Target.
- c) **Access Control.** The TOE enforces access control policy to restrict access to user data. The TOE ensures that documents, document processing job information, and security-relevant data are accessible only to authenticated users who have the appropriate access permissions.
- d) **Storage Data Encryption.** The TOE encrypts data on the HDD and in NVRAM to protect documents and confidential system information if those devices are removed from the TOE.
- e) **Identification and Authentication.** Except for a defined minimal set of actions that can be performed by an unauthenticated user, the TOE ensures that all users must be authenticated before accessing its functions and data. Users login to the TOE by entering their credentials on the local operation panel, through WIM login, through print or fax drivers, or using network authentication services.
- f) **Administrative Roles.** The TOE provides the capability for managing its functions and data. Role-based access controls ensure that the ability to configure the security settings of the TOE is available only to the authorized administrators. Authenticated users can perform copy, printer, scanner, document server and fax operations based on the user role and the assigned permissions.
- g) **Trusted Operations.** The TOE performs power-on self-tests to ensure the integrity of the TSF components. It provides a mechanism for performing trusted update that verifies the integrity and authenticity of the upgrade software before applying the updates.
- h) **TOE Access.** Interactive user sessions at the local and remote user interfaces are automatically terminated by the TOE after a configured period of inactivity.
- i) **Trusted Communications.** The TOE protects communications from its remote users using TLS/HTTPS. The TOE can be configured to use TLS to protect communication with the syslog, LDAP and SMTP servers.
- j) **PSTN Fax-Network Separation.** The TOE restricts information received from or transmitted to the telephone network to only fax data and fax protocols. It ensures that the fax modem cannot be used to bridge the LAN.
- k) **Image Overwrite.** the TOE actively overwrites residual image data stored on the HDD after a document processing job has been completed or cancelled.

10

NOTE: No claims are made regarding any other security functionality.

1.3.4 Evaluation Assumptions

11

The following assumptions were made in performing the Common Criteria evaluation. The guidance shown in the table below should be followed to uphold these assumptions in the operational environment.

Table 4: Evaluation Assumptions

Assumption	Guidance
A.PHYSICAL — Physical security, commensurate with the value of the TOE and the data it stores or processes, is assumed to be provided by the environment.	Ensure that the device is hosted in a physically secure environment and that adequate security measures are in place to protect access.
A.NETWORK — The Operational Environment is assumed to protect the TOE from direct, public access to its LAN interface.	Ensure that the device is hosted on a protected network environment.
A.TRUSTED_ADMIN — TOE Administrators are trusted to administer the TOE according to site security policies	Ensure that administrators are trustworthy – e.g. implement background checks or similar controls.
A.TRAINED_USERS — Authorized Users are trained to use the TOE according to site security policies	Ensure that authorized users receive adequate training.

1.4 Conventions

12 The following conventions are used in this guide:

- a) CLI Command `<replaceable>` - This style indicates to you that you can type the word or phrase on the command line and press [Enter] to invoke a command. Text within `<>` is replaceable. For example:
Use the `cat <filename>` command to view the contents of a file
- b) [key] or [key-combo] – key or key combination on the keyboard is shown in this style. For example:
The [Ctrl]-[Alt]-[Backspace] key combination exits your graphical session and returns you to the graphical login screen or the console.
- c) **GUI => Reference** – denotes a sequence of GUI screen interactions. For example:
Select **File => Save** to save the file.
- d) [REFERENCE] *Section* – denotes a document and section reference from Table 5. For example:
Follow [ADMIN] *Configuring Users* to add a new user.

1.5 Related Documents

13 This guide supplements the below documents which are available on the [Ricoh Support site](#) help pages.

Table 5: Related Documents

Reference	Document
[ADMIN]	User Guide IM 550/600 Series User Guide
[SECURITY]	User Guide IM 550/600 Series Security Guide
[SECURITY REFERENCE]	User Guide IM 550/600 Series User Guide Security Reference
[FIRMWARE]	User Guide IM 550/600 Series Checking Firmware Validity
[WEB IMAGE MONITOR]	User Guide IM 550/600 Series Using Web Image Monitor
[REGISTER ADMINISTRATOR]	User Guide IM 550/600 Series Registering Administrators Before Using the Machine
[PREPARE SERVER]	User Guide IM 550/600 Series Preparing the Server to Use for User Authentication
[LDAP SERVER]	User Guide IM 550/600 Series Programming the LDAP Server
[FAX]	User Guide IM 550/600 Series Registering Fax Numbers in the Address Book
[LOGS]	User Guide IM 550/600 Series Collecting Logs
[USER MANAGEMENT]	User Guide IM 550/600 Series Introduction and Basic Operations

14

NOTE: The information in this guide supersedes related information in other documentation.

2 Secure Acceptance and Update

2.1 Obtaining the TOE

15 The TOE is delivered via commercial carrier.

2.2 Verifying the TOE

16 To verify the TOE Model, check that the machine's model number on the label to the rear of the machine ends with -17, -27, -29 or -51 which correspond to the branding variants of IM 550/600 series included in the evaluated configuration.

17 To verify the TOE firmware, the authorized administrator login and use the following steps:

18 On the Operation Panel:

- a) -Press [Settings]
- b) -Press [Machine Features Settings]
- c) -Press [System Settings]
- d) -Press [Administrator Tools]
- e) -Press [Firmware version]

The firmware list is displayed

On the WIM:

- a) -Device Management -> Configuration->Firmware Update

This lists all the firmware except for the TPM device driver which is only shown in the Ops panel firmware listing.

2.3 Power-on Self-Tests

19 At system start-up, the TOE performs a firmware validity test to determine if the firmware is valid. If an error occurs and the test fails, a verification error is displayed on the control panel. The firmware validity test error will also display on the Web Image Monitor after the machine starts.

20 The TOE also performs software integrity test at TOE start-up by verifying the digital signature on the TOE software. Any errors are displayed on the Control Panel or on the WIM interface.

21 Additional details on the Power-on self-tests can be found online in Taking Measures to Prevent Security Threats.

2.4 Updating the TOE

22 TOE updates are hand delivered by Ricoh service personnel. The update packages are digitally signed and uploaded to the TOE using WIM.

23 For MFP Control or FCU Software, the TOE performs the following verifications installing the package:

- a) Identifies the type of software (e.g., MFP Control, Operation Panel, FCU);

- b) Verifies that the software model name matches the TOE;
- c) Verifies the digital signature on the update package.

1 For Operation Panel software, the TOE performs the following verifications before the installing the package:

- a) Identifies the type of software (e.g., MFP Control, Operation Panel, FCU);
- b) Verifies that the software model name matches the TOE;
- c) Verifies the digital signature

3 Configuration Guidance

3.1 Installation

24 The TOE is delivered pre-installed with initial settings for CC-mode configuration performed by a Ricoh Authorized Service representative. CC conformance requires an authorized service representative to perform the initial setup of the TOE.

3.1.1 Printer and Fax Driver

25 The printer and LAN-Fax driver are downloaded from Ricoh support site. To install the printer driver, enter the machine's IP address or host name in the [URL] box as follows:

`https://(machine's IP address or host name)/printer`

26 To install the LAN-Fax driver, enter the following URL in the [Printer URL] box as follow:

`https://(machine's IP address or host name)/printer`

27 Install the LAN-Fax driver (INF file) in the following location:

28 32-bit driver

29 X86\DRIVERS\LAN-FAX\X86\DISK1

30 64-bit driver

31 X64\DRIVERS\LAN-FAX\X64\DISK1

3.2 Administration Interfaces

32 The TOE provides the following administrator interfaces:

- a) **Operation Panel of the MFP** is an LCD touch screen interface that provides a local user interface where users can perform copy, fax print, network transmission of documents operations. The administrator user can configure the MFP via this local interface.
- b) **Web Image Monitor (WIM)** this is the remote user interface accessible via TLS/HTTPS where users can perform print, copy, fax, storage operations on documents. This interface provides various settings for administrators to perform limited configuration of the MFP.


3.3 Initial Configuration

33 Both the Operation Panel and the WIM are used to setup initial configuration of the MFP TOE. Authorized administrator must be registered during the initial setup by entering a username/password combination. Procedures 1 through 3 describe the sequential steps for initial configuration of the TOE.

34 Change the screen type from "Classic" to "Standard" in "Switch Screen Type" in "Administrator Tools" in "System Settings" in "Settings" and reboot the machine.

35 The following warnings are noted:

- a) Before using the MFP, the encryption key to encrypt the data in the machine must be provided by the service representative or be newly created.
- b) Back up the encryption key only when the machine is not operating.

- c) Security attributes are modified at the time they are submitted to the system with the "OK" button. Currently logged in user's access rights will be updated at this time, and it is unnecessary to logout and log back in for the access changes to be reflected.
- d) For faxing, use the public switched telephone network. IP-Fax and Internet Fax are not CC conformant.
- e) For print jobs and fax transmissions from the client computer, use IPP-SSL authentication.
- f) If the message "SD Card authentication has failed" is displayed, contact Ricoh Service Representative.
- g) In the event of a hard disk error, the machine will display options to initialize the disk or not. Note that user authentication might fail after a hard disk initialization, if this happens, contact the service representative.
- h) To send files by e-mail using the scanner or fax function, install the user certificate when registering a user in the address book and set the encryption setting to [Encrypt All]. When you display addresses to send an e-mail, a  icon will appear next to destinations for which [Encrypt All] has been set.
- i) Before receiving faxes, specify "Stored Reception File User Setting" in the Fax setting.
- j) When you configure "Program Special Sender" in the fax mode, do not specify "Forwarding per Sender" or "Memory Lock RX per Sender" before registering or changing special senders.
- k) The file creator (owner) has the authority to grant [Full Control] privileges to other users for stored documents in the Document Server. However, administrators should tell users that [Full Control] privileges are meant only for the file creator (owner).
- l) When using Web Image Monitor, users should not access other Web sites. Users should logout of WIM when it is not being used.
- m) Obtain log files by downloading them via Web Image Monitor or by automatic log collection.
- n) To prevent incorrect timestamps from being recorded in the audit log, ensure that the Audit Server that connects to the MFP is synchronized with the MFP.
- o) If the power plug is pulled out before the main power is turned off so that the machine is shut down abnormally, the date and time when the main power is turned off (the value for "Main Power Off", which is an attribute of the eco log) is not registered correctly to the "eco" log.
- p) When you specify "HDD Erase Method" in "Erase All Memory", do not select "Format".
- q) Do not assign "Reception File Settings" to a Quick Operation key in Fax mode.
- r) When you delete all logs, make sure that the following functions are not being used:
 - i) Scan file transmission
 - ii) When switching from \ [On] to [Off] in [Document Server Function] in [Administrator Tools] in [System Settings], delete all the received fax documents and specify the following settings again:

1. System Settings
2. Administrator Tools -> File Management -> Document Server Function -> Select [On]
3. Fax Settings
4. Reception Settings -> Reception File Settings -> Store [On]
5. Reception Settings -> Reception File Settings -> Print [Off]

3.3.1 Procedure 1 – Settings using the Operation Panel

36 Follow the instructions in “[Registering Administrators Before Using the Machine](#)” to activate the administrator account that would configure the machine. Enter passwords for administrator and supervisor, these are the authorized administrators roles that comprise U.ADMIN and the only roles with permissions to configure the TOE and the TSF.

37 Login to the operation panel as the administrator to configure the settings below.

38 Delete all icons on the Home screen except for “Copy”, “Scanner”, “Fax” “settings”, “Quick Print Release”, “Printer”, “Document Server”, “Address Book”, “fax RX File Widget” and “Change Language” Do not re-register the deleted icons.

39 Uninstall the following applications according to [Uninstalling an Application] in [Installing an Application from Application Site] in [Introduction and Basic Operations].

- CAP Java Card Plug-in
- CAP NFC Plug-in
- CAP [uma]-G2 Plug-in
- CAP User Config.
- CAP V2 Auth. UI
- ELP NX

3.3.1.1 System Settings

40 The administrator must specify the settings in [System Settings] within the ranges shown in Table 6.

Table 6: System Settings 1

Tab	Item	Settings
Wireless & networks	Interface Settings ▶ Interface Settings	[Wi-Fi Connection]
Wireless & networks	Proxy Settings ▶ Use Proxy	[OFF] (Clear)
Wireless & networks	Wi-Fi	[OFF] (Clear)

Tab	Item	Settings
Wireless & networks	Wireless Direct Settings	[OFF] (Clear)
Wireless & networks	Bluetooth	[OFF] (Clear)
Personal	Security ▶ Setting for Entering Authentication Password ▶ Characters to be Used for Entering Password	[Only 1 Byte Characters]
System	Screen Device Settings ▶ Screen SD Card Slot	[Inactive]
System	Screen Device Settings ▶ Screen USB Memory Slot	[Inactive]
System	Screen Device Settings ▶ Server Settings ▶ Server Function ▶ Server Function	[Inactive]
System	Screen Device Settings ▶ External Interface Software Settings ▶ Select IC Card Reader	[Do not Use]
System	Screen Device Settings ▶ User's Own Customization	[Prohibit]
Timer Settings	Time Zone	Set the appropriate time zone. The specified setting is applied after the machine reboots.

Tab	Item	Settings
Timer Settings	Daylight Saving Time	<p>Set the appropriate daylight saving time.</p> <p>The specified setting is applied after the machine reboots. Reboot the machine after configuring this setting.</p>
Timer Settings	Set Date	Set the appropriate date.
Timer Settings	Set Time	Set the appropriate time.
Timer Settings	Auto Logout Timer	<p>Select [On], and then set the range for the timer between 10-999 seconds.</p> <p>Note: The auto-logout timer is interfered with by the Timer setting 'auto-sleep timer". The 'auto-sleep timer' will turn off the unit after the time has elapsed. Basically, the lower of the two timer settings ('auto-logout' and 'auto-sleep') will log the user out. Set the same range of minutes for both settings.</p>
Interface Settings	Network/USB ▶ Machine IPv4 Address Configuration	<p>Specifying a static IPv4 address</p> <p>Enter the IPv4 address and subnet mask.</p> <p>Obtaining the DHCP server address automatically</p> <p>Select [Auto-Obtain (DHCP)].</p>
Interface Settings	Network/USB ▶ IPv4 Gateway Address	Enter the IPv4 gateway address.

Tab	Item	Settings
Interface Settings	Network/USB ▶ DNS Configuration	Specify this only if you are using a static DNS server. Specifying a static DNS server Enter the IPv4 address in "DNS Server 1", "DNS Server 2", and "DNS Server 3". (Specify DNS Server 2 and 3 if required.) Obtaining the DHCP server address automatically Select [Auto-Obtain (DHCP)].
Interface Settings	Network/USB ▶ Effective Protocol ▶ IPv4	[Active]
Interface Settings	Network/USB ▶ Effective Protocol ▶ IPv6	[Inactive]
Interface Settings	Network/USB ▶ SMB Client Advanced Settings ▶ SMBv2/SMBv3	[Inactive]
File Transfer	Fax Email Account	[Do not Receive]
Administrator Tools	Administrator Authentication Management ▶ User Management	Set [Administrator Authentication] to [On], and then select [Administrator Tools] in [Available Settings].
Administrator Tools	Administrator Authentication Management ▶ Machine Management	Set [Administrator Authentication] to [On], and then select [General Features], [Tray Paper Settings], [Timer Settings], [Interface Settings], [File Transfer], and [Administrator Tools] in [Available Settings].

Tab	Item	Settings
Administrator Tools	Administrator Authentication Management ▶ Network Management	Set [Administrator Authentication] to [On], and then select [Interface Settings], [File Transfer], and [Administrator Tools] in [Available Settings].
Administrator Tools	Administrator Authentication Management ▶ File Management	Set [Administrator Authentication] to [On], and then select [Administrator Tools] in [Available Settings].
Administrator Tools	▶ Program/Change Administrator ▶ Administrator 1-4	Specify settings for one or more administrators. Specify the administrator's "Login User Name" and "Login Password".
Administrator Tools	▶ Program/Change Administrator ▶ Set Administrator Privileges	Assign all administrator roles (user administrator, machine administrator, network administrator, and file administrator) to a single administrator.
Administrator Tools	▶ Program/Change Administrator ▶ Supervisor	Change the supervisor's "Login User Name" and "Login Password". Note: This operation can only be performed by the supervisor.
Administrator Tools	Media Slot Use ▶ Store to Memory Device	[Prohibit]
Administrator Tools	Media Slot Use ▶ Print from Memory Storage Device	[Prohibit]
Administrator Tools	Extended Security ▶ Restrict Display of User Information	[On]
Administrator Tools	Extended Security	[On]

Tab	Item	Settings
	▶ Restrict Use of Destinations (Fax)	
Administrator Tools	Extended Security ▶ Restrict Use of Destinations (Scanner)	[On]
Administrator Tools	Extended Security ▶ Transfer to Fax Receiver	[Prohibit]
Administrator Tools	Extended Security ▶ Authenticate Current Job	[Access Privilege]
Administrator Tools	Extended Security ▶ Update Firmware	[Prohibit]
Administrator Tools	Extended Security ▶ Change Firmware Structure	[Prohibit] After specifying this setting, be sure to click [OK].
Administrator Tools	Extended Security ▶ Password Policy	<p>Set "Complexity Setting" to [Level 1] or [Level 2], press [Change] on the right of "Minimum Character No.", and then set the number of characters to 15 or more.</p> <p>For example, to set the number of characters to 15, press the number key "1", "5", and then "#".</p> <p>Even if you change the password policy, passwords that have already been registered can still be used. The changed password policy will be applied only to passwords specified or changed subsequently.</p> <p>Regardless of policy settings, all passwords are obfuscated during password entry.</p>
Administrator Tools	Extended Security	[Off]

Tab	Item	Settings
	▶ Security Setting for Access Violation	
Administrator Tools	Auto Delete File in Document Server	Select [Specify Days], [Specify Hours] or [Off]
Administrator Tools	LDAP Search	[Off]
Administrator Tools	Service Mode Lock	[On]
Administrator Tools	Auto Erase Memory Setting	<p>Select [On], and then select [NSA], [DoD], or [Random Numbers].</p> <p>If you set this to [Random Numbers], set [Number of Erase] to three or more.</p>
Administrator Tools	Transfer Log Setting	<p>[Do not Forward]</p> <p>Log forwarding will be configured in the WIM as specified in section 3.3.3 below.</p>
Administrator Tools	Machine Data Encryption Settings	<p>Ensure that the current data has been encrypted.</p> <p>If the data has been encrypted, the following message will appear: "The current data in the machine has been encrypted."</p>
Administrator Tools	Central Management ▶ Address Book	[Do not Manage Centrally]
Administrator Tools	Application Authentication Management	Set [Copier Function], [Printer Function], [Document Server Function], [Fax Function] and [Scanner Function] to [On].
Administrator Tools	Document Server Function	Select [On]
Administrator Tools	Menu Protect	[Level 2]

3.3.1.2 User Authentication Settings

41 The TOE supports local authentication labeled 'Basic Authentication' or external authentication labeled [LDAP Authentication], using an LDAP Server in its operational environment. The TOE supports both methods of user authentication, but both cannot be enforced on the same running instance of the TOE. The authorized administrator specifies the settings for user authentication in "User Authentication Management" -> "Administrator Tools" -> "System Settings". The administrator configures the active authentication methods as Basic Authentication options using the following settings:

3.3.1.2.1 Basic Authentication Settings

Table 7: Basic Authentication

Tab	Item	Settings
Administrator Tools	User Authentication Management	[Basic Authentication.]
Administrator Tools	User Authentication Management ▶ Basic Authentication. ▶ Available Functions	Specify this in accordance with your operating environment. Set the browser to [Unavailable].
Administrator Tools	User Authentication Management ▶ Basic Authentication. ▶ Printer Job Authentication	[Entire]

3.3.1.2.2 LDAP Authentication Settings

42 Prior to configuring the LDAP Authentication settings, an LDAP server must be configured and available for used by the TOE. For details on preparing the LDAP Server in the operational environment, see the [Security Guide](#) Section '[Preparing the Server to Use for User Authentication](#)' and the Settings section "[Programming the LDAP Server](#)".

Table 8: LDAP Authentication

Tab	Item	Settings
Administrator Tools	User Authentication Management	[LDAP Authentication]

Tab	Item	Settings
Administrator Tools	User Authentication Management ▶LDAP Authentication. ▶LDAP Servers	Select the LDAP server to authenticate.
Administrator Tools	User Authentication Management ▶LDAP Authentication. ▶Available Functions	Specify this in accordance with your operating environment. Set the browser to [Unavailable].
Administrator Tools	User Authentication Management ▶LDAP Authentication. ▶Printer Job Authentication	[Entire]

3.3.1.3 Printer Settings

43 The administrator must configure the printer settings within the range specified in Table 9.

Table 9: Printer Settings

Tab	Item	Settings
Data Management	Menu Protect	[Level 2]
Data Management	List / Test Print Lock	[On]
Data Management	Auto Delete Temporary Print Jobs	Select [On] or [Off].
Data Management	Auto Delete Stored Print Jobs	Select [On] or [Off].
Data Management	Jobs Not Printed As Machine Was Off	[Do not Print]

Tab	Item	Settings
Data Management	Auto Store Jobs without User Authentication Information	Select [Off]

3.3.1.4 Scanner Settings

44 The administrator must configure the scanner settings must be set within the range specified in Table 10.

Table 10: Scanner Settings

Tab	Item	Settings
Initial Settings	Menu Protect	[Level 2]
General Settings	Print & Delete Scanner Records	[Do not Print: Delete Oldest] or [Do not Print: Disable Send]
General Settings	Download File Directly From URL Link	[Off] Note: If [Download File Directly from URL Link] in [General Settings] in [Scanner Settings] is set to [Off], the URL of the scanned and stored files cannot be sent by e-mail.

3.3.1.5 Fax Settings

45 The administrator must configure the fax settings within the range specified in Table 11.

Table 11: Fax Settings

Tab	Item	Settings
General Settings	Box Setting	Set all items to [* Not Programmed].
Send Settings	Backup File TX Setting	[Off]
Reception Settings	Reception File Settings ▶ Store	[On]

Tab	Item	Settings
Reception Settings	Reception File Settings ▶ Forwarding	[Off]
Reception Settings	Reception File Settings ▶ Print	[Off]
Reception Settings	Reception File Settings ▶ Memory Lock Reception	[Off]
Initial Settings	Menu Protect	[Level 2]
Detailed Initial Settings	Parameter Setting ▶ switch 40, bit 0	[1] If the memory for stored received faxes become full, the MFP stops receiving new faxes and keeps the stored ones without printing or deleting them.
Detailed Initial Settings	Parameter Setting ▶ switch 10, bit 0	[1] Only users who are authorized by the administrator can access, from the control panel, received faxes that are stored.
Detailed Initial Settings	Parameter Setting ▶ switch 04, bit 7	[0] If this is enabled, previews will not be included in the reports.
Detailed Initial Settings	Internet Fax Setting	[Off]
Detailed Initial Settings	Email Setting	[Off]
Detailed Initial Settings	Folder Setting	[Off]

3.3.2 Procedure 2 – Using the Web Image Monitor (WIM)

46

The administrator login to the WIM interface using a web browser from a client computer to configure values for various MFP settings including Device, Printer, Fax,

Network, Security and Webpage. For details on launching the WIM interface see the Using Web Image Monitor page in the User Guide.

3.3.2.1 Device Settings

47 The administrator sets the values in [Device Settings] as specified in Table 12.

Table 12: Device Settings

Category	Item	Settings
Device Settings	System ▶ Prohibit printing stored files from Web Image Monitor	[Prohibit]
Device Settings	Logs ▶ Collect Job Logs	[Active]
Device Settings	Logs ▶ Job Log Collect Level	[Level 1]
Device Settings	Logs ▶ Collect Access Logs	[Active]
Device Settings	Logs ▶ Access Log Collect Level	[Level 2]
Device Settings	Logs ▶ Collect Eco-friendly Logs	[Active]
Device Settings	Logs ▶ Eco-friendly Log Collect Level	[Level 2]
Device Settings	Logs ▶ Common Settings for All Logs ▶ Transfer Logs	[Inactive]

Category	Item	Settings
Device Settings	SYSLOG Transfer ▶ Transfer SYSLOG Server	[Active] Note: Syslog server in the TOE operational environment must be capable of reading RFC 6587 conformant record types.
Device Settings	Email ▶ Administrator Email Address	Enter the administrator's email address.
Device Settings	Email ▶ SMTP Server Name	Enter the SMTP server name or IP address.

3.3.2.2 Printer Settings

48 On the WIM interface, the administrator configures the settings for [printer] with the values specified in Table 13.

Table 13: Printer Settings

Category	Item	Settings
Printer	Basic Settings ▶ Virtual Printer	[Inactive]
Printer	Permissions for Printer Language to Operate File System ▶ PDF,PostScript	[Do not Permit]
Printer	Google Cloud Print Settings ▶ Google Cloud Print	Select [Off], and then press [Start registration].

3.3.2.3 Fax Settings

49 On the WIM interface, the administrator configures the settings for [Fax] with the values specified in Table 14.

Table 14: Fax Settings

Category	Item	Settings
Fax	IP-Fax Settings ▶ Enable H.323	[Off]
Fax	IP-Fax Settings ▶ Enable SIP	[Off]
Fax	Parameter Settings ▶ LAN-Fax Result Report	[Off]

3.3.2.4 Network Settings

50 The administrator login to the WIM to configures the network settings listed in Table 15.

Table 15: Network Settings

Category	Item	Settings
Network	IPv4 ▶ LLMNR	[Inactive]

3.3.2.5 Security Settings

- 51 The TOE includes FIPS validated cryptographic module which it uses to provide its cryptographic services. The TOE uses TLSv1.2 for remote administration via WIM and for communication with remote non-administrative users. TLSv1.2 is also used for communication with Syslog and SMTP and LDAP servers.
- 52 If the TLS channel for remote administration is broken unintentionally, the MFP will attempt to re-establish the connection automatically or by prompting the user to retry manually.
- 53 While the trusted channel to a remote syslog server is disrupted, the TOE will store audit records locally on the MFP up to the document storage limits. Once the disruption has been corrected the TOE will automatically resume transmission. All LDAP user authentication attempts will be denied while the trusted channel to an LDAP server is disrupted.
- 54 All pre-shared keys, symmetric keys, and private keys are encrypted and are not accessible through normal interfaces during operation. Instructions for clearing the machine before disposal are provided in the [Security Guide](#).
- 55 The TOE stores keys and certificates in encrypted form in NVRAM and Flash memory. Destruction of old keys is performed directly without delay in NVRAM; in

Flash, it is performed by an internal microcontroller in concert with wear-leveling, bad block management, and garbage collection processes. There are no situations where key destruction may be delayed at the physical layer.

3.3.2.5.1 Cryptographic Settings –

56 The authorized administrator must configure the following cryptographic parameters using the WIM.

Table 16: Security Settings

Category	Item	Settings
Security	Device Certificate ▶ Certificate 1 ▶ Create	Configure this to create and install the device certificate (self-signed certificate) Set "Algorithm Signature" to one of the following: sha512WithRSA-4096 sha512WithRSA-2048 sha256WithRSA-4096 sha256WithRSA-2048 See the Security Guide for the other necessary settings.

Category	Item	Settings
Security	Device Certificate ▶Certificate 1 ▶Request	<p>Configure this to create the request form for the certificate authority to issue the device certificate.</p> <p>If you are using a self-signed device certificate, you do not need to configure this setting.</p> <p>Of the settings for the device certificate (certificate issued by the certificate authority), set "Algorithm Signature" to one of the following:</p> <ul style="list-style-type: none"> sha512WithRSA-4096 sha512WithRSA-2048 sha256WithRSA-4096 sha256WithRSA-2048 <p>Submit the application form to request that the certificate authority issue the device certificate.</p> <p>The request method depends on the certificate authority. For details, contact the certificate authority.</p> <p>You can install the certificate issued by the certificate authority via Web Image Monitor.</p>
Security	Device Certificate ▶Install	<p>To use the device certificate (issued by the certificate authority), install the certificate by configuring this setting.</p> <p>If using the intermediate certificate as well, install that too.</p>
Security	Device Certificate ▶Install Intermediate Certificate	<p>When using an intermediate certificate, configure this setting to install the certificate.</p>
Security	Device Certificate ▶Certification ▶S/MIME	<p>Select the installed device certificate.</p>

Category	Item	Settings
Security	Network Security ▶ Security Level	[FIPS 140] After setting this to [FIPS 140], be sure to click [OK].
Security	Network Security ▶ TCP/IP ▶ IPv6	[Inactive]
Security	Network Security ▶ HTTP - Port 80 ▶ IPv4	[Close] Doing this will also set "IPv4" to [Close] in "Port 80" in "IPP".
Security	Network Security ▶ SSL/TLS Version	Set "TLS1.2" to [Active], and "TLS1.3", "TLS1.1" and "TLS1.0" to [Inactive].
Security	Network Security ▶ Encryption Strength Setting	Check "AES128" and/or "AES256", and uncheck "3DES".
Security	Network Security ▶ TCP/IP ▶ KEY EXCHANGE ▶ RSA	[Inactive]
Security	Network Security ▶ TCP/IP ▶ DIGEST ▶ SHA1	[Inactive]
Security	Network Security ▶ FTP ▶ IPv4	[Inactive]

Category	Item	Settings
Security	Network Security ▶WSD (Device) ▶IPv4	[Inactive]
Security	Network Security ▶WSD (Printer)	[Inactive]
Security	Network Security ▶WSD (Scanner)	[Inactive]
Security	Network Security ▶SNMP	[Inactive]
Security	S/MIME ▶Encryption Algorithm	Select [AES-256 bit], or [AES-128 bit]. When using S/MIME, it is necessary to register the user certificate. Note: It is mandatory to ensure that certificate has an email address RDN that matches the email address the user used in Table 12.
Security	S/MIME ▶Digest Algorithm	Select [SHA-512 bit], [SHA-384 bit], or [SHA-256 bit].
Security	User Lockout Policy ▶Lockout	[Active]
Security	User Lockout Policy ▶Number of Attempts before Lockout	1-10
Security	User Lockout Policy ▶Lockout Release Timer	[Active]

Category	Item	Settings
Security	User Lockout Policy ▶ Lock Out User for	1-9999

3.3.2.6 Wim Auto Logout Settings

57 The administrator must configure the values for [Webpage] settings as specified in Table 17.

Table 17: Wim Auto Logout Settings

Category	Item	Settings
Webpage	Webpage ▶ Web Image Monitor Auto Logout Settings	3 – 60 minutes Note that the default setting is 60 minutes.

3.3.3 Procedure 3 – Additional Settings on the Operation Panel

58 After completing the configurations in Procedure 2 using the WIM interface, the administrator must go back to the Operation Panel and login to continue with the following settings.

3.3.3.1 System Settings

59 The administrator must configure the values for [System] settings specified in Table 18.

Table 18: System Settings 2

Tab	Item	Settings
System	Screen Device Settings ▶ Application Authentication Settings ▶ General Settings for Application Authentication	Select [Auth. Not Required] for all applications.
Interface Settings	Network/USB ▶ Effective Protocol ▶ Firmware Update (IPv4)	[Inactive]

Tab	Item	Settings
Interface Settings	Network/USB ▶ Effective Protocol ▶ Firmware Update (IPv6)	[Inactive]
Interface Settings	Network/USB ▶ Effective Protocol ▶ @Remote Service	[Inactive]

3.3.3.2 Fax Settings

60 The administrator must configure in the address book the users and groups who are authorized to receive faxes stored by the MFP. See the User Guide Section on 'Registering Fax Numbers in the Address Book'. After users are entered in the address book, the administrator can configure the Fax settings in Table 19.

Table 19: Fax Settings

Tab	Item	Settings
Reception Settings	Stored Reception File User Setting	[On] After setting this to [On], specify the users or groups that can access stored reception files.

3.3.4 Verifying the MFP Settings

- 61 After completing procedure 1 through procedure 3, check the log data and ROM version with the following steps:
- a) Check that the machine is OFF
 - b) Turn the machine ON.
 - c) Check the details of the Log files that were stored in the machine. Check that the details for "Log Type", "Result", and "Module Name" in the recorded access log are as follows:
 - i) Log Type: Firmware: Structure
 - ii) Result: Succeeded
 - iii) Module Name: G3
 - iv) For additional details about logs, see "[Collecting Logs](#)", "Managing Devices", settings.

- d) Login as admin to the Operation Panel and check the fax parameter settings with the following steps:
 - i) Press [Settings]
 - ii) Press [Fax Settings]
 - iii) Press [Detailed Initial Settings]
 - iv) Press [Parameter Settings: Print List]
 - v) Check that the following ROM version matches the one shown in the printed list: [ROM Version]
G3: 08.00.00 (Validation Data: 44B9)
- e) Log off

3.4 Services

3.4.1 Firewall

62 See System Settings

3.4.2 Syslog Server

63 See Table 12: Device Settings. For additional information see "[Collecting Logs](#)" in the online User Guide.

3.4.3 LDAP Server

64 [Programming the LDAP Server](#) in the Settings page of the online User Guide provides instructions for configuring the LDAP server that the TOE will use for user authentication. Server information to be configured includes:

- a registration name for the LDAP server
- host name or IPv4 address of the LDAP server
- a root folder to store email addresses
- port number used for communication with the LDAP server (636)
- Use Secure Connection (SSL) is set to [ON]
- Digest Authentication

65 Additional settings for the LDAP server are described in Table 8: LDAP Authentication.

66

3.4.4 CAC/PIV Authentication Solutions

67 For CAC/PIV authentication, follow the installation and configuration guidance in CAC/PIV/SIPR v4.1 Installation & Configuration Guide and CAC PIV SIPR ELPNX SOP Option v2.3 Installation Guide for v4.x.

3.5 Administration

3.5.1 Administration Interfaces

68 The TOE provides the following administrator interfaces:

- c) **Operation Panel of the MFP** is an LCD touch screen interface that provides a local user interface where users can perform copy, fax print, network transmission of documents operations. The administrator user can configure the MFP via this local interface.
- d) **Web Image Monitor (WIM)** this is the remote user interface accessible via TLS/HTTPS where users can perform print, copy, fax, storage operations on documents. This interface provides various settings for administrators to perform limited configuration of the MFP.

Table 20 below shows the management functions available at the different administration interfaces:

Table 20: Management Functions

Management Functions	Enable	Interface(s)
Manage user accounts (users, roles, privileges and available functions list)	Create, modify, delete	Operation Panel, WIM
Manage the document user list for stored documents	Create, modify	Operation Panel, WIM
Configure audit transfer settings	Modify	WIM
Manage audit logs	Query, delete, export	Operation Panel, WIM
Manage Audit Functions	Enable, Disable	Operation Panel, WIM
Manage time and date settings	Modify	Operation Panel, WIM
Configure minimum password length	Modify	Operation Panel, WIM
Configure Password complexity settings	Modify	Operation Panel, WIM
Configure Operation Panel Auto Logout Time	Modify	Operation Panel, WIM
Configure WIM Auto Logout Time	Modify	WIM
Configure number of authentication failure before account lockout	Modify	WIM
Configure account release timer settings	Modify	WIM
Configure PSTN Fax-Line Separation Stored Reception File User	Modify	Operation Panel
Configure image overwrite	Modify	Operation Panel

Management Functions	Enable	Interface(s)
Configure network settings for trusted communications (specify IP addresses and port to connect to the TOE)	Modify	Operation Panel, WIM
Manage HDD Cryptographic key	Create Delete	Operation Panel
Manage Device Certificates	Create, query, modify, delete, upload, download	Operation Panel, WIM
Manage TOE Trusted Update	Query, Modify	WIM
Configure SMTP over TLS	Modify	WIM
Configure LDAP over TLS	Modify	Operation Panel, WIM
Configure syslog over TLS	Modify	WIM
Manage user accounts (Ability to login)	Unlock	WIM

3.6 Management of Security Functions

69 After initial configuration the TOE security functions can be modified and managed via the WIM or the Operation Panel.

3.6.1 Functions Managed via the Operation Panel

70 The following settings are available via Operation Panel to manage the TOE time services, network services, administrators, the password policy and the auto erase memory function.

Table 21: Changing System Settings

Tab	Item	Settings
Timer Settings	Time Zone	Set the appropriate time zone. The specified setting is applied after the machine reboots.

Tab	Item	Settings
Timer Settings	Daylight Saving Time	<p>Set the appropriate daylight saving time.</p> <p>The specified setting is applied after the machine reboots. Reboot the machine after configuring this setting.</p>
Timer Settings	Set Date	Set the appropriate date.
Timer Settings	Set Time	Set the appropriate time.
Timer Settings	Auto Logout Timer	<p>Select [On], and then set the range for the timer between 10-999 seconds.</p>
Interface Settings	Network/USB ▶ Machine IPv4 Address	<p>Specifying a static IPv4 address</p> <p>Enter the IPv4 address and subnet mask.</p> <p>Obtaining the DHCP server address automatically</p> <p>Select [Auto-Obtain (DHCP)].</p>
Interface Settings	Network/USB ▶ IPv4 Gateway Address	Enter the IPv4 gateway address.
Interface Settings	Network/USB ▶ DNS Configuration	<p>Specify this only if you are using a static DNS server.</p> <p>Specifying a static DNS server</p> <p>Enter the IPv4 address in "DNS Server 1", "DNS Server 2", and "DNS Server 3". (Specify DNS Server 2 and 3 if required.)</p> <p>Obtaining the DHCP server address automatically</p> <p>Select [Auto-Obtain (DHCP)].</p>
Administrator Tools	Program/Change Administrator ▶ Administrator 1-4	<p>Specify settings for one or more administrators.</p> <p>Specify the administrator's "Login User Name" and "Login Password".</p>

Tab	Item	Settings
Administrator Tools	Program/Change Administrator ▶Set Administrator Privileges	Assign all administrator roles (user administrator, machine administrator, network administrator, and file administrator) to a single administrator.
Administrator Tools	Program/Change Administrator ▶Supervisor	Change the supervisor's "Login User Name" and "Login Password". Note: You must be login as the Supervisor admin to change the login information for the supervisor admin.
Administrator Tools	Extended Security ▶Password Policy	Set "Complexity Setting" to [Level 1] or [Level 2], press [Change] on the right of "Minimum Character No.", and then set the number of characters to 15 or more. For example, to set the number of characters to 15, press the number key "1", "5", and then "#". Changes to the password policy apply to passwords that are specified or changed after the policy has been updated.
Administrator Tools	Auto Erase Memory Setting	Select [On], and then select [NSA], [DoD], or [Random Numbers]. If you set this to [Random Numbers], set [Number of Erase] to three or more.
General Settings	Print & Delete Scanner Journal	[Do not Print: Delete Oldest] or [Do not Print: Disable Send]

3.6.2 Functions Managed via the WIM

71 The following settings are used to manage TOE functions via the WIM interface.

3.6.2.1 SMTP Settings

72 The TOE provides secure communication with an SMTP server. Use the following settings to manage the SMTP server.

Table 22: SMTP Settings

Category	Item	Settings
Device Settings	Email ▶ Administrator Email Address	Enter the administrator's email address.
Device Settings	Email ▶ SMTP Server Name	Enter the SMTP server name or IP address.

3.6.2.2 Security Settings

73 The following settings available on the WIM interface are used to manage the TOE cryptographic and trusted channel functions as well as the user lockout policy.

Table 23: Changing Security Settings

Category	Item	Settings
Security	Device Certificate ▶ Certificate 1 ▶ Create	<p>Configure this to create and install the device certificate (self-signed certificate).</p> <p>If you are using a certificate issued by the certificate authority, you do not need to configure this setting.</p> <p>Of the settings for the device certificate (self-signed certificate), set "Algorithm Signature" to one of the following:</p> <ul style="list-style-type: none"> sha512WithRSA-4096 sha512WithRSA-2048 sha256WithRSA-4096 sha256WithRSA-2048

Category	Item	Settings
Security	Device Certificate ▶Certificate 1 ▶Request	<p>Configure this to create the request form for the certificate authority to issue the device certificate.</p> <p>If you are using a self-signed device certificate, you do not need to configure this setting.</p> <p>Of the settings for the device certificate (certificate issued by the certificate authority), set "Algorithm Signature" to one of the following:</p> <ul style="list-style-type: none"> sha512WithRSA-4096 sha512WithRSA-2048 sha256WithRSA-4096 sha256WithRSA-2048 <p>Submit the application form to request that the certificate authority issue the device certificate.</p> <p>The request method depends on the certificate authority. For details, contact the certificate authority.</p> <p>You can install the certificate issued by the certificate authority via Web Image Monitor.</p>
Security	Device Certificate ▶Install	<p>To use the device certificate (issued by the certificate authority), install the certificate by configuring this setting.</p> <p>If using the intermediate certificate as well, install that too.</p>
Security	Device Certificate ▶Install Intermediate Certificate	<p>When using an intermediate certificate, configure this setting to install the certificate.</p>
Security	Device Certificate ▶Certification ▶S/MIME	<p>Select the installed device certificate.</p>

Category	Item	Settings
Security	S/MIME ▶Encryption Algorithm	Select [AES-256 bit] or [AES-128 bit]. When using S/MIME, it is necessary to register the user certificate.
Security	S/MIME ▶Digest Algorithm	Select [SHA-512 bit], [SHA-384 bit], or [SHA-256 bit].
Security	User Lockout Policy ▶Number of Attempts before Lockout	1-10
Security	User Lockout Policy ▶Lock Out User for	1-9999

3.6.2.3 Auto Logout Settings

74 The TSF initiated termination function can be managed via the WIM with by configuring the value for the following setting.

Table 24: Auto Logout Settings

Category	Item	Settings
Webpage	Webpage ▶Web Image Monitor Auto Logout Settings	3 – 60 minutes Note that the default setting is 60 minutes.

3.6.3 User Management

75 Users accessing the TOE functions are identified and authenticated and allowed to access only the functions that they have permissions to access. The TOE includes an address book of registered users accounts that stores individual user attributes including username, user role, available function lists. The instructions for managing users are provided in [Registering a User in the Address Book and Specifying the Login Information](#).

3.6.4 Administrator Roles

76 The System Settings in Procedure 1 include the settings for managing the administrator roles.

3.6.5 Default Passwords

77 The administrator and supervisor passwords are blank by default and must be set during initial configuration.

3.6.6 Password Management

78 The System Settings in Procedure 1 above includes settings to configure the password policy.

3.6.7 Audit Logging

79 The TOE collects audit data in 3 types of logs:

- a) Job log – which logs user actions such as printing, copying, storing documents or faxing documents.
- b) Access Log - which logs identification and authentication events, system events and security operations events. This log includes records of the use of the management functions, login and logout events.
- c) Eco -Friendly Log — Which logs power on and power off events.

80 Only the authorized administrator can access, configure and manage the audit settings. Only the authorized administrator can review and manage the audit logs

81 The TOE limits the number of audit records that it stores in the 3 logs: 4000 job logs, 12,000 access logs and 4,000 eco-friendly logs before the oldest audit record are overwritten. Using the WIM the authorized administrator can download the audit logs and delete them.

82 Additional instructions for managing the audit logs are available in the [Collecting Logs](#) Ricoh Help pages,

3.7 U_NORMAL User Access

83 The U_Normal user does not have administrator access to the TOE. They can access TOE protected user data and functions based on the available functions list configured for their user account. The user guide describes the job and operations accessible to the U_Normal user.

4 Clearing the machine for redeployment or at end-of-life

84 All pre-shared keys, symmetric keys, and private keys are encrypted and are not accessible through normal interfaces during operation.

85 To clear the machine of all customer-supplied information, perform the following steps:

- a) Replace the data encryption key
- b) Replace the device certificate
- c) Perform the Erase All Memory function

86 This deletion function is outside the scope of the evaluation. See the [Security Guide](#) for additional information.

Requirement	Auditable Events	Example Event
		<pre> "Print", "2020-09-02T17:21:08.0", "2020-09-02T17:21:14.0", "1", "LT", "normal",,, Fax: "2020-09-03T09:24:06.0", "2020-09-03T09:24:54.0", "Fax: Sending", "Failed", "Control Panel", "Failed", "Cancelled by User", "0x00000003", "u1", "0x0000000001b364" ,,, Succeeded, "Completed", "0x000000000001b364" ,,, Scan File, "2020-09-03T09:24:09.0", "2020-09-03T09:24:10.0", "Failed", "Failed", "Data Transfer Interrupted", "0x000000000001b364" ,,, Send, "2020-09-03T09:24:06.0", "2020-09-03T09:24:54.0", "u1d", "1234", "Succeeded", "Completed", "0x00000003", "u1", "0x000000000001bee9" ,,, Scan: "2020-09-09T16:52:36.0", "2020-09-09T16:52:47.0", "Scanner: Sending", "Succeeded", "Control Panel", "Completed", "0x00000003", "u1", "0x000000000001bee9" ,,, Succeeded, "Completed", "0x000000000001bee9" </pre>

Requirement	Auditable Events	Example Event
		<pre> "Scan File", "2020-09- 09T16:52:36.0", "2020-09- 09T16:52:40.0" "Completed", "Succeeded", "0x000000000001bee9", "Send", "2020- 09-09T16:52:40.0", "2020-09- 09T16:52:47.0", "u1d", "10.20.5.7 :/u1" Document Server: "2020-09-03T09:13:24.0", "2020- 09-03T09:13:28.0", "Document Server: Storing", "Succeeded", "C ontrol Panel", "Completed", "0x0 0000003", "u1", "0x00000000000 1b349" "Completed", "Succeeded", "0x000000000001b349", "Scan File", "2020-09- 03T09:13:24.0", "2020-09- 03T09:13:28.0" "Completed", "Succeeded", "0x000000000001b349", "Store", "2020- 09-03T09:13:24.0", "2020-09- 03T09:13:28.0", "903", "COP Y0012", "0" Copy: "2020-09-01T12:41:09.0", "2020- 09- 01T12:41:19.0", "Copier: Copyin g", "Succeeded", "Control Panel", "Completed", "0x00000003", "u1" "0x000000000001adf4" </pre>

Requirement	Auditable Events	Example Event
		<pre> "Scan File", "2020-09- 01T12:41:09.0", "2020-09- 01T12:41:19.0" ,Succeeded", "Completed" ,"0x000000000001adf4" ,"Scan File", "2020-09- 01T12:41:09.0", "2020-09- 01T12:41:19.0" ,"LT", "normal" </pre>
<p>FIA_UAU.1/ FIA_UID.1</p>	<p>Unsuccessful identification Unsuccessful authentication</p>	<pre> Operation Panel "2020-09-03T09:13:00.0", "2020-09- 03T09:13:00.0", "Login", "Failed", ,"Password Mismatch", "0x00000000", "u1", " 0x0000000000001b347", "Auth entication", "Control Panel" ,"Completed" WIM "2020-09-09T16:35:58.0", "2020-09- 09T16:35:58.0", "Login", "Failed", ,"Password Mismatch", "0x00000000", "admi n", "0x000000000001bea1", "ip:1 72.16.200.10", "Authentication", " "via Network" </pre>

Requirement	Auditable Events	Example Event
		<pre> C ompleted" </pre>
FMT_SMF.1	Use of a management function	<pre> Setting authentication lockout policies: "2020-08-26T14:58:16.0","2020- 08-26T14:58:16.0","Machine Configuration","Succeeded",,"Su cceded",,"0xfffff88","admin1",," 0x000000000000195bf",,""Device Settings" "User Lockout Policy" "Completed" "0x000000000000195bf" "Device Settings" "Num ber of Attempts before Lockout" "4" "Completed" "0x000000000000195bf" "Device Settings" "Lock Out User for" "2" "Completed" </pre>

Requirement	Auditable Events	Example Event
		<pre> 0000 0000 0000 0000 0000 0000 0000 0000 0 0 00 0 0 00 0 0 0 0 0 0 0 0 0000 0000 0 0 00000 </pre>
FTP_TRP.1 Remote non-admin users	Failure to establish a session	See remote administration
FTP_ITC.1	Failure to establish a session	TLS: <pre> {"parentLogId":"0000000000018f5f", "subLogId":"000800000000006500000000000018f5f", "subJobType":"destination.network", "desNetSubState":"ended-incomplete", "desNetStartTime":"2020-08-25T20:29:51Z", "desNetStartValidTimeFlag":"on", "desNetEndTime":"2020-08-25T20:30:01Z", "desNetEndValidTimeFlag":"on", "desNetAddressName":"u1d", "desNetAddress":"u1@example.com", "desNetSendKind":"mail", "desNetSendOwner":"u1d", "desNetSendMode":"document", "desNetSendPages":"","desNetFileNo":"","desNetErrorInfo":"","desNetSubStatusDetail":"dest-connect-fail", "logPart":"1of1"} </pre>